BENZA®

GENERATOR

BZ1000iS

GENERATOR SPECIFICATIONS

Max. output	kW	1.1
Rated speed	rpm	3,000
Frequency	Hz	50
Rated Voltage	V	230
Noise level	dB(A)	89

ENGINE SPECIFICATIONS

Engine manufacturer		Benza
Fuel		Petrol
Displacement	cc	60
Maximum power	HP	2
Nº. of cylinders		1
Starting system		Recoil
Fuel tank capacity	L	3.6
Autonomy (75%)	H	6

ALTERNATOR SPECIFICATIONS

Alternator brand		Benza Inverter
Poles	Nº.	2
Voltage regulator		Capacitor
Earth circuit breaker		Yes
Single phase sockets	Nº.	1 unit of 230V – 4,4A
DC sockets 12V		1 unit of 6,5 A

SINGLE PHASE

50HZ

PETROL

MANUAL START

STANDARD ACCESORIES

Oil sensor
Earth circuit breaker
Inverter technology

DIMENSIONS & WEIGHT

Length	mm	450
Width	mm	240
Height	mm	380
Weight	kg	13,5



internaco

15680 Órdenes (La Coruña) · España
Tel. +34 981 680 101 · Fax +34 981 680 353
contactcenter@internaco.com · www.internaco.com
export@internaco.com · www.benza.es